

Dial Lamp Specifications

Part Number	Size	Volts	Amps	Candle Power	Filament Shape	Average Life (hrs)	Lamp #	Lamp Type
P-49	T-3 1/4	2.0	0.06	0.04	S-2	1,000	49	Bayonet
P-48	T-3 1/4	2.0	0.06	0.04	C-2R	1,000	48	Screw
P-43	T-3 1/4	2.5	0.50	0.50	C-2R	3,000	43	Bayonet
P-41	T-3 1/4	2.5	0.50	0.50	C-2R	3,000	41	Screw
P-45	T-3 1/4	3.2	0.35	0.50	C-2R	3,000	45	Bayonet
P-42	T-3 1/4	3.2	0.35	0.50	C-2R	3,000	42	Screw
P-47	T-3 1/4	6.3	0.15	0.50	C-2R	3,000	47	Bayonet
P-40	T-3 1/4	6.3	0.15	0.50	C-2R	3,000	40	Screw
P-44	T-3 1/4	6.3	0.25	0.90	C-2R	3,000	44	Bayonet
P-46	T-3 1/4	6.3	0.25	0.90	C-2R	3,000	46	Screw
P-50	G-3 1/2	7.5	0.22	1.00	C-2R	1,000	50	Screw
P-51	G-3 1/2	7.5	0.22	1.00	C-2R	1,000	51	Bayonet
P-52	G-3 1/2	14.4	0.10	0.75	C-2V	1,000	52	Screw
P-53	G-3 1/2	14.4	0.12	1.00	C-2V	1,000	53	Bayonet
P-55	G-4 1/2	7.0	0.41	2.00	C-2R	500	55	Bayonet
P-57	G-4 1/2	14.0	0.24	2.00	C-2V	500	57	Bayonet
P-81	G-6	6.5	1.02	6.00	C-2R	500	81	Bayonet